

- 1 -

METHOD OF PROCESSING IMAGE SIGNAL FROM SOLID-STATE  
IMAGING DEVICE, IMAGE SIGNAL PROCESSING APPARATUS,  
IMAGE SIGNAL GENERATING APPARATUS AND COMPUTER PROGRAM  
PRODUCT FOR IMAGE SIGNAL PROCESSING METHOD

BACKGROUND OF THE INVENTION

The present invention relates to a method of processing the color component signal (image signal) obtained from a solid-state image pickup device, an  
5 image signal processing apparatus, an image signal generating apparatus comprising the image signal processing apparatus and the solid-state image pickup device, and a computer program product for the image signal processing method.

10 The solid-state image pickup device or the image sensor has a two-dimensional arrangement of a plurality of photoelectric elements such as photodiodes. For example, both the three primary color signals such as R, B and G signals and the luminance  
15 signal are produced in a single-chip solid-state image pickup device. A monochromatic color filter of R (red light penetrating), G (green light penetrating) or B (blue light penetrating) is arranged on the light-receiving surface of each photoelectric element. A  
20 white filter (a filter of white light penetrating) is arranged in place of the G filter in some cases. A plurality of photoelectric elements including these three types of color filters are arranged on the light-

0067448 092800

Generally, the color component signals composed of all the three primary colors are required from each pixel for producing high quality full-color image signals. In the single-chip solid-state image pickup device, however, only a monochromatic color component signal corresponding to the color of the filter of a respective photoelectric element of a pixel can be produced in each pixel. In each pixel of a given color in the single-chip solid-state image pickup device the two remaining color component signals are produced in such a manner that the signals from the adjacent pixels having different color filters are subjected to the signal processing such as interpolation.

20           An example of the image signal processing  
method as described above is disclosed in US Patent No.  
5,382,976. This US patent describes a signal  
processing method for a single image sensor including a  
red pixel, a green pixel and a blue pixel. For the red  
25 pixel or the blue pixel not including the green  
component, the green value is obtained by interpolating  
the signal values of the pixels adjacent to the  
particular pixel. Also, the US patent includes the

description to the effect that with regard to the green value of phase "00" containing the green value or phase "11", the adjacent pixel values are not interpolated but the signal values of the phases are used as they are without interpolation as indicated by  $G = G(0,0)$  in Figs. 4A and 4B of the U.S. patent.

Now, a specific example of an image signal processing method will be explained with reference to the drawings.

10                Fig. 2 is a diagram showing an example a block configuration of an image signal processing apparatus comprising a single-chip solid-state image pickup device and various processing circuits for processing the image signal picked up by the solid-  
15                state image pickup device. In Fig. 2, reference numeral 1 designates a solid-state image pickup device such as a charge-coupled device (CCD) image sensor for converting the imaging light into electric charge and outputting it as a video signal, numeral 2 a sample-  
20                hold and automatic gain control (CDS&AGC) circuit (CDS: Correlated Double Sampling) for sample holding the video signal outputted from the CCD 1 and outputting the video signal by amplifying the sample hold signal to a required level, and numeral 3 an A/D converter for  
25                converting the analog video signal from the CDS&AGC circuit 2 into a digital video signal.

                Numeral 4 designates a DSP (digital signal processor) circuit for processing the video signal from

0967118-092800

The color filters of the solid-state image pickup device (CCD) 1 are arranged in Bayer arrangement pattern. Fig. 3A shows the Bayer arrangement pattern and the arrangement of the pixel addresses attached to the pixels. In Fig. 3A, a green light transmitting filter (a filter of green light penetrating) is designated as G, a red light transmitting filter (a filter of red light penetrating) as R and a blue light transmitting filter (a filter of blue light penetrating) as B. Further, the number 1 is attached to the highest row and the leftmost column. For example, the pixel address of a pixel having a green light transmitting filter located on the mth row from top and the nth column from left is expressed as  $G_{m,n}$ . The symbol of the pixel address is also expressed as the value of the color component signal obtained by picking up an image in the particular pixel.

A method of image signal processing for the green component signal constituting one of the processes executed in the DSP circuit 4 described above will be explained with reference to Fig. 4C showing an example of the pixel interpolation method. The method (i) or (ii) described below is adaptively used for each pixel address. Specifically, in method (i), as for the green component signal level of a pixel address (e.g.  $G_{22}$ ) having a green light transmitting filter, the value of the green component signal level of the particular

pixel address is used as it is. In method (ii), on the other hand, as for the green component signal level of a pixel address (e.g.  $R_{23}$ ) having a red light transmitting filter or the green component signal level of a pixel address (e.g.  $B_{34}$ ) having a blue light transmitting filter, the average value of the green component signal levels obtained from the pixels (e.g.  $G_{13}$ ,  $G_{22}$ ,  $G_{24}$ ,  $G_{33}$ ) having a green light transmitting filter at the upper, lower, left and right adjacent pixel addresses is used.

A specific example of the signal processing method (ii) described above will be explained in more detail. As shown in Fig. 4C, in the case where the image signal is processed for the pixel address  $R_{23}$  to generate the green component signal level  $g_{23}$  by interpolation, for example, the value is calculated from

$$g_{23} = (G_{13} + G_{22} + G_{24} + G_{33})/4 \quad (1)$$

Another method of calculation included in the signal processing method (ii) uses the values of only the left and right adjacent pixels of the pixel address  $R_{23}$  as shown in equation (2) below for calculation.

$$g_{23} = (G_{22} + G_{24})/2 \quad (2)$$

Various other alternative methods are conceivable including a method in which only the upper and lower adjacent pixel values or only the diagonally adjacent pixel values of the pixel address  $R_{23}$  are used for calculation.

003260"STT7960

Fig. 4A is a diagram showing an interpolation method for the R component signal at the position of the pixel address  $G_{22}$ . In this case, the red component signal at the position of  $G_{22}$  has a pixel level equal to the average of the imaging red component signal levels of the pixel address  $R_{21}$  and the pixel address  $R_{23}$ . Fig. 4B is a diagram showing an interpolation method for the B component signal at the position of the pixel address  $G_{22}$ . In this case, the blue component signal at the position of  $G_{22}$  has a pixel level equal to the average of the imaging blue component signal levels of the pixel address  $B_{12}$  and the pixel address  $B_{32}$ . Further, Fig. 4D is a diagram showing an interpolation method for the B component signal at the position of the pixel address  $R_{23}$ . In this case, the blue component signal at the position of  $R_{23}$  has a pixel level equal to the average of the imaging blue component signal levels at the respective positions of the pixel addresses  $B_{12}$ ,  $B_{14}$ ,  $B_{32}$  and  $B_{34}$ .

The signal processing method described above has the following problem. Specifically, assume that the band limiting range of the source follower circuit of the amplifier 15 of the output unit of the CCD used for securing the required S/N ratio, the bandwidth of the CDS circuit 2 or the band limiting range of the process amplifier is excessively narrow. Then, the waveform of the output signal is distorted in each case. As a result, a horizontal line having the blue

008260" 8TT 2960

light transmitting filter such as the (m-1)th line  
(row) in Fig. 3A and the horizontal line having the red  
light transmitting filter such as the mth line (row) in  
Fig. 3A have different waveform distortion amounts of  
5 the green component signal. Thus, the error levels  
applied to the green component signals are different  
between adjacent lines, often resulting in variations  
of the green component signal level, even when a  
uniform green component light in the imaging light is  
10 applied from the object to each pixel. The green  
component signals varied from one line to another  
causes horizontal stripes of noises on the image  
subjected to the signal processing as shown in Fig. 4C.

Also, in the case where the conditions for  
15 the production process undergo a change, the filter  
characteristic of the green light transmitting filter  
among the CCD color filters may be varied in every  
other horizontal scanning line, i.e. between a  
horizontal line having the blue light transmitting  
20 filter and a horizontal line having the red light  
transmitting filter, which often causes variations of  
the green component signal level between different  
lines.

This often leads to the problem that even  
25 when a uniform green component light in the imaging  
light is applied from an object to each pixel, the  
levels of the green component signals corresponding to  
the pixels of the green light transmitting filters

0957448-092300

Figs. 6A and 6B show waveforms obtained by sampling the output signal of the CCD in a correlated double sampling (CDS) circuit when the CCD having the aforementioned problem picks up an object having a uniform brightness and color in a whole picture frame. Fig. 6A shows a signal waveform of a horizontal line (the mth horizontal line in Fig. 3A, for example)

15 In Figs. 6A and 6B, numerals 100, 200  
designate reference voltage signal (for example, an  
optical black signal) waveforms. Numeral 110  
designates an image signal waveform corresponding to  
the reference voltage signal waveform 100, and numeral  
20 210 designates an image signal waveform corresponding  
to the reference voltage signal waveform 200. The  
values of the color component signals of the image  
signal waveforms 110, 210 are indicated by the level  
difference with the reference voltage signal waveforms  
25 100, 200, respectively. In the waveform 110, from left  
to right, the level waveforms of the red component  
signal, the green component signal and the red  
component signal are shown, while in the waveform 210,



from left to right, the level waveforms of the green component signal, the blue component signal and the green component signal are shown.

Comparison between the green component signal of the waveform 110 in Fig. 6A and the green component signal of the waveform 210 in Fig. 6B shows that the signal levels are different between them due to the problem described above. In the case where an image is displayed on a monitor (not shown) inserted in a subsequent stage, this level difference is seen to cause a level difference between horizontal lines even in a displayed image produced by imaging an object uniformly. Thus the image is displayed in horizontal stripes or speckles, thereby extremely deteriorating the image quality.

#### SUMMARY OF THE INVENTION

The object of the present invention is to provide means for preventing the unnecessary level difference from being caused between horizontal lines or reducing the unnecessary level difference even in the case where the picking up characteristics of the CCD are varied or the performance thereof is deteriorated and thereby to prevent the deterioration of the image quality which otherwise might be caused by horizontal stripes or speckles on a picked-up image or a part of image by the imaging light from the object.

According to one aspect of the invention,

0067118-092800

there is provided an image signal processing method for processing the color component signals obtained from a solid-state image pickup device including an arrangement of a plurality of photoelectric elements with color filters arranged in the light receiving section of the photoelectric elements, comprising the steps of fetching a color component signal from a designated pixel corresponding to the photoelectric element located on a line and having a filter that can transmit the green light in the solid-state image pickup device, fetching the color component signals from the pixel corresponding to the photoelectric element on other pixel line than the first line of the designated pixel in the neighborhood of the designated pixel, the neighboring pixels each having a filter for transmitting at least the green light, and determining the value of the color component signal of the designated pixel corresponding to the photoelectric element having the filter that can transmit at least the green light, based on a plurality of the color signals fetched in the foregoing steps.

According to another aspect of the invention, there is provided an image signal processing apparatus for processing the color component signals obtained by a solid-state image pickup device including an arrangement of a plurality of photoelectric elements and a color filter arranged in the light receiving section of each pixel corresponding to the

008260" 877960

photoelectric element comprising means for fetching the color component signal from a designated pixel corresponding to the photoelectric element having a filter that can transmit at least the green light on the lines of the solid-state image pickup device, means for fetching the color component signal from a pixel corresponding to the photoelectric element on other pixel line than said line of the designated pixel in the neighborhood of the designated pixel, the neighboring pixels each having a filter for transmitting at least the green light, and arithmetic means for determining the value of the color component signal of the designated pixel corresponding to the photoelectric element having the filter that can at least the green light, based on a plurality of the color signals fetched.

According to still another aspect of the invention, there is provided an image signal generating apparatus comprising a solid-state image pickup device including an arrangement of a plurality of photoelectric elements and a color filter arranged in the light receiving section of each pixel corresponding to the photoelectric element, and an image signal processing unit for processing the color component signals obtained by the solid-state image pickup device, wherein the signal processing unit includes means for fetching the color component signal from a designated pixel corresponding to the photoelectric

09671118-092800

003250" 8TF 2960

element located on a line of the solid-state image pickup device and having a filter that can transmit at least the green light, means for fetching the color component signals from the pixel corresponding to the

5 photoelectric element located on other lines in the neighborhood of the designated pixel, the neighboring pixels each having a filter capable of transmitting at least the green light, and arithmetic means for determining the value of the color component signal of

10 the designated pixel corresponding to the photoelectric element having a filter capable of transmitting at least the green light, based on a plurality of the color signals fetched.

According to a further aspect of the

15 invention, there is provided a computer program product comprising a computer usable medium having computer readable program code means embodied therein for processing the color component signals obtained by a solid-state image pickup device having an arrangement

20 of a plurality of photoelectric elements with a color filter arranged in the light receiving section of each of the pixels corresponding to the photoelectric elements, wherein the computer readable program code means includes means for fetching the color component

25 signal from a designated pixel corresponding to the photoelectric element located on a line of the solid-state image pickup device and having a filter that can pass at least the green light, means for fetching the

color component signals from the pixel corresponding to the photoelectric element in the neighborhood of the designated pixel and located on line different from the designated pixel, the neighboring pixels being located  
5 on lines and each having a filter capable of transmitting at least the green light, and means for determining the value of the color component signal of the designated pixel corresponding to the photoelectric element having a filter capable of passing at least the  
10 green light, based on a plurality of the color signals fetched.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Figs. 1A and 1B are diagrams for explaining an example of an image signal processing method  
15 according to the invention.

Fig. 2 is a diagram showing an example block configuration of an image signal processing apparatus.

Figs. 3A and 3B are diagrams showing the Bayer arrangement pattern and another arrangement of  
20 filters, i.e. pixel addresses attached to the pixels.

Figs. 4A, 4B, 4C and 4D are diagrams for explaining an example of the pixel interpolation method.

Figs. 5A and 5B are diagrams showing the  
25 level of the green component signal of each pixel for the image signal processing method according to the invention.

0967118-092800

5            Fig. 7 is a block diagram showing an image  
signal generating apparatus including a signal  
processing apparatus according to an embodiment of the  
invention.

Fig. 9 shows an example of the main flowchart for interpolation of the green component signal in a signal processing apparatus according to the invention.

20            Fig. 11 shows an example of the flowchart for the signal processing performed by a signal processing apparatus according to this invention even in the case of a filter arrangement other than the Bayer arrangement pattern shown in Fig. 3B.

25                    Fig. 12 is a flowchart schematically showing  
the signal processing steps for a signal processing  
apparatus according to the invention.

Embodiments of the invention will be explained below. A block configuration of an image signal processing apparatus according to the invention

15           An image signal processing method, i.e. a  
method of processing the green component signal which  
is one of the processes carried out in a DSP circuit 40  
according to the invention will be explained with  
reference to Figs. 1A, 1B and the flowcharts of Figs. 9  
20 to 12 showing an example of the image signal processing  
method according to the invention.

Fig. 9 shows the main routine of the image signal processing in the DSP 40 of a signal processing apparatus according to an embodiment of the invention. First, in step 101, the video signals of all the pixel addresses of an image frame to be interpolated are stored in a frame buffer memory 41 from an A/D converter 3. As an alternative, the video signal of a

pixel address  $G_{m,n}$  corresponding to a green light transmitting filter of the image frame is stored in the frame buffer memory 41.

In step 102, an interpolation process is carried out in an interpolation processing unit 42 for determining the green component value among the three color component signal values at the respective positions of the green pixel, the red pixel and the blue pixel. Hereinafter, the green pixel means a pixel corresponding to the photoelectric element provided with a color filter transmitting at least green light, the red pixel means a pixel corresponding to the photoelectric element provided with a color filter transmitting red light, and the blue pixel means a pixel corresponding to the photoelectric element provided with a color filter transmitting blue light. The green pixel may be replaced by a white pixel having a white filter which transmits green light and other particular color component light. A specific flow of the process performed in step 102 will be explained with reference to the interpolation processing flows shown in Figs. 10 and 11. In step 103, it is determined whether the interpolation processing is complete for all the pixel addresses in an image frame intended for interpolation, and the process of steps 102 and 103 is repeated until the value of the green component is determined for all the pixel addresses.

Now, a specific subroutine of step 102 will



First, in the interpolation method shown in Fig. 1A, the signal value of the green pixel is determined by method (i') described below in accordance with the pixel address. Further, method (ii) is adaptively applied for each of red and blue pixel addresses.

In a specific example of application of method (i') described above, as shown in Fig. 1A, consider the case in which a green component signal level  $g_{22}$  is obtained by the processing the image signal for the pixel address  $G_{22}$ . The value is calculated from

This equation can be rewritten into a general expression below.

25           In the method shown in Fig. 1B, on the other  
hand, the method (i") described below is carried out in  
accordance with the pixel address followed by  
adaptively carrying out the method (ii) described

above.

(i") The green component signal of a pixel address  $G_{m,n}$  having a green light transmitting filter is a weighted average of the value of the green component signal picked up in the particular pixel and the values of the green component signals obtained in the pixels having a green light transmitting filter at the four pixel addresses  $G_{m-1,n-1}$ ,  $G_{m-1,n+1}$ ,  $G_{m+1,n-1}$ ,  $G_{m+1,n+1}$  diagonally upper and lower than the particular pixel address  $G_{m,n}$ .

As a specific example, as shown in Fig. 1B, for example, assume that the green component signal level  $g_{22}$  is to be obtained by image signal processing for the pixel address  $G_{22}$ . The value is calculated as shown below,

$$g_{22} = (G_{11} + G_{13} + G_{22} + G_{31} + G_{33})/5 \quad (5)$$

or by weighting pixel address  $G_{22}$  more than other pixel addresses as shown below.

$$g_{22} = (G_{11} + G_{13} + 4G_{22} + G_{31} + G_{33})/8 \quad (6)$$

Equations (5) and (6) can be rewritten into general expressions shown below.

$$g_{mn} = (\alpha G_{m-1,n-1} + \beta G_{m-1,n+1} + \gamma G_{m,n} + \delta G_{m+1,n-1} + \epsilon G_{m+1,n+1})/\omega, \quad (7)$$

where  $\omega = \alpha + \beta + \gamma + \epsilon$ .

Fig. 10 is a flowchart for the aforementioned interpolation processing method according to an embodiment. This flow is a flow of the interpolation

00360"8TT2960

processing of step 102 in the main flow shown in Fig.  
9. First, in step 201, the pixel address of the pixel  
intended for interpolation is designated. Assume that  
the designated pixel address is  $G_{m,n}$  ( $m, n$ : positive  
5 integers). In step 202, it is determined whether the  
designated pixel address is that of the pixel having a  
green (white) light transmitting filter or not. In the  
case where the designated pixel is not a green (white)  
pixel, the pixel data is read from the frame memory 41  
10 and the data values of the red and blue pixels are  
determined by equation (1), (2) or (2') in step 203.  
In the case where the designated pixel is a green  
(white) pixel, on the other hand, the pixel data are  
read from the frame memory 41 and the data value of the  
15 green pixel is determined according to equation (4) or  
(7) in step 204.

Various other calculation methods than the  
methods (i') and (i'') are conceivable for the image  
processing method according to the invention.

20 In the pattern of Fig. 1A, for example, the  
green signal value of the designated pixel address  $G_{m,n}$   
may be determined using the average value of the upper  
right pixel address  $G_{m-1,n+1}$  and the lower left pixel  
address  $G_{m+1,n-1}$  each adjacent to the pixel address  $G_{m,n}$ .  
25 Also, the green pixel on a horizontal line other than  
the upper and lower adjacent horizontal lines can be  
used as the green signal value of the designated pixel  
address  $G_{m,n}$ .

The signal processing method and apparatus according to the invention described above are not limited to the image pickup device having the Bayer arrangement pattern, but is also applicable to other patterns of arrangement. For example, Fig. 11 shows a flowchart of interpolation for the color filter arrangement pattern shown in Fig. 3B. This flow is a routine in step 102 of the main flow shown in Fig. 9.

First, the pixel address of the pixel intended for interpolation is designated in step 301. Assume that the designated pixel address is  $G_{m,n}$  ( $m, n$ : positive integers). In step 302, it is determined whether the designated pixel address is that of a pixel having a green (white) light transmitting filter or not. In the case where the designated pixel is not a green (white) one, the pixel data is read out from the frame memory 41 and the data values of the red and blue pixels are determined according to equation (2) in step 303. In the case the designated pixel is a green (white) pixel, on the other hand, the pixel data is read out from the frame memory 41 and the data value of the green pixel is determined in accordance with equation (4) or (8) in step 304. Here, equation (8) is disclosed below.

$$g_{mn} = (\alpha G_{m-2,n} + \beta G_{m-1,n} + \gamma G_{m,n} + \delta G_{m+1,n} + \epsilon G_{m+2,n}) / \omega \quad (8)$$

, where  $\omega = \alpha + \beta + \gamma + \delta + \epsilon$ .

Fig. 12 is a flowchart showing the interpolation processing of step 102 in Fig. 9, i.e. the flow of Figs. 10 and 11 in broader term. Steps 401, 402 are similar to steps 201, 202, respectively, in Fig. 10. In step 403, the green component signal value  $g_{mn}$  in the red pixel and the green component signal value  $g_{mn}$  in the blue pixel are determined using the green (white) video signal component value obtained from the pixel of a green (white) light transmitting filter among those pixels adjacent to the pixel of the designated pixel address or the average of the predetermined green (white) component signal value. Further, in step 404, the green component signal value  $g_{mn}$  of the green pixel is determined from the average of the green (white) component signal value obtained from the pixel of the designated pixel address and the green (white) component signal value obtained from at least one pixel of green (white) light transmitting filter among those pixels adjacent to the particular designated pixel.

The behavior of the image signal level in the case of the image processing is conducted using an example of the image processing method according to the invention described above will be explained with reference to Figs. 5A and 5B. Figs. 5A and 5B show the level of the green component signal of each pixel while omitting the level of the red component signal and the

blue component signal.

Figs. 5A and 5B are diagrams showing, in a matrix for each pixel address, the behavior of the green component signal (image signal) before and after the processing of an image picked up from a uniform object using the method of Fig. 1A according to the invention. Fig. 5A shows the image signal level picked up before the image processing according to the invention, and Fig. 5B shows the image signal level obtained as the result of the image processing according to the invention.

Fig. 5A shows the manner in which the green component signal level assumes different values of 140 and 100 between odd rows, i.e. horizontal lines having a blue light transmitting filter and even rows, i.e. horizontal lines having a red light transmitting filter. In contrast, Fig. 5B shows the manner in which the image signal processing is conducted so that the green component signal level value is 120 for both odd rows, i.e. the horizontal lines having a blue light transmitting filter and even rows, i.e. the horizontal lines having a red light transmitting filter.

The reason why the value of the green component signal level is 120 for both cases is that the image signal processing by the use of the method shown in Fig. 1A produces a green component signal level value 120 obtained by an average of 140 and 100 which are signal levels before the interpolation.

5 aforementioned interpolation technique.

The flowcharts shown in Figs. 9, 10, 11 and 12 according to embodiments of the invention can be stored in any of various media (not shown) such as a magnetic disk, an optical disk and a semiconductor memory in the form of a program code readable by the computer or the microprocessor, and the program is read from the recording medium by the DSP 40 or the personal computer 43 thereby to execute the steps of the flowchart. Also, the program code can be downloaded to the DSP 40 or the personal computer 43 through a communication channel (not shown) to carry out the signal processing method according to the invention.

It will thus be understood from the foregoing description that according to this invention, even in the case where the green component signal level is different between odd and even horizontal scanning lines due to the variations of the CCD characteristics or the performance deterioration thereof, the image quality deterioration can be prevented and a clear image can be produced without causing a horizontal striped pattern or speckles on a picked-up image or a part of image by the imaging light from the object by preventing the unnecessary level difference from occurring between horizontal lines or reducing such level difference.

008260 " 877950